

INSTALLATION INSTRUCTIONS

Item#N1513-613

READ AND SAVE THESE INSTRUCTIONS

WARNING! SHUT POWER OFF AT FUSE OR CIRCUIT BREAKER.
VERTISSEMENT! COUPER LE COURANT AU NIVEAU DES FUSIBLES OU DU DISJONCTEUR.

PREPARATION THE FIXTURE

1. Shut off power at the fuse box or circuit breaker box and remove the old fixture including the mounting hardware.
2. Carefully unpack your new fixture and lay out all the parts in a clean area. Take care not to misplace any small parts necessary for installation.
3. Position mounting plate (A) on ceiling and mark location of the four mounting holes. Pre-drill holes for plastic anchors (Y). Insert plastic anchors (Y) into ceiling.
4. Attach mounting plate (A) to junction box (Not included) using junction box screws (O). The side of mounting plate marked "GND" must face out.
5. Secure mounting plate (A) by inserting wood screws (C) through holes on mounting plate (A) into plastic anchors (Y).

CONNECTING THE WIRES

6. Connect the electrical wires as shown in Fig.2. Making sure that all wire connectors (F) are secured. If your junction box has a ground wire (green or bare copper), connect fixture's ground wire to it. Otherwise, connect fixture's ground wire directly to mounting plate (A) using green screw provided.

COMPLETING THE INSTALLATION

7. Attach canopy (B) to mounting plate (A) and tighten with canopy screws (D).
8. Install (3) three medium base bulbs (J) up to 40 watts or CFL or LED equivalent (not included) in accordance with the fixture's specification. **DO NOT EXCEED THE MAXIMUM WATTAGE RATING! (NE PAS DEPASSER LA PUISSANCE NOMINALE MAXIMALE!).**
9. Carefully hang the fixture body (G) to the hooks on canopy (B).

Your installation is now complete. Return power to the junction box and test the fixture.

Note: Illustration (Fig. 1) on this manual is for installation purposes only. It may or may not be identical to the fixture purchased.

The fixture is over 10 lbs. Please remove fixture body (G) before removing canopy from mounting plate to inspect wire connections in the future. This will allow you to hold the fixture body during wire connection inspection or fixture removal.

Fig 1.

