

INSTALLATION INSTRUCTIONS

Item#291-732

READ AND SAVE THESE INSTRUCTIONS

WARNING! SHUT POWER OFF AT FUSE OR CIRCUIT BREAKER.

AVERTISSEMENT! COUPER LE COURANT AU NIVEAU DES FUSIBLES OU DU DISJONCTEUR.

PREPARATION (Fig. 1)

1. Shut off power at the fuse box or circuit breaker box and remove the old fixture including the mounting hardware.
2. Carefully unpack your new fixture and lay out all the parts in a clean area. Take care not to misplace any small parts necessary for installation.
3. Attach mounting plate (A) to the junction box (not included) with junction box screws (B) (Size: #8-32N*L1"). The side of the mounting plate (A) with "GND" marked on it and two convex points must face out.

ASSEMBLING THE FIXTURE (Fig. 1 & Fig. 3)

4. Loosen the screw (E), adjust desired cord (H) length and fasten the screw (E) until snug.

CONNECTING THE WIRES (Fig. 2)

5. Connect the electrical wires as shown in fig.2, making sure that all wire connectors are secured. If junction box has a ground wire (green or bare copper), connect the fixture's ground wire to it. Otherwise, connect the fixture's ground wire directly to mounting plate (A) using the green screw provided. Tuck the wire connectors neatly into the junction box.

COMPLETING THE INSTALLATION (Fig. 1)

6. Raise canopy (C) to junction box and secure with mounting screws (D).
7. Install (1) one medium base bulb up to 60 watts each or CFL or LED equivalent (not included) in accordance with the fixture specification—**DO NOT EXCEED THE MAXIMUM WATTAGE RATING! (NE PAS DEPASSER LA PUISSANCE NOMINALE MAXIMALE!)**
8. Secure glass shade (G) on fixture (F), Do not over tighten.

Your installation is now complete. Return power to the junction box and test the fixture.

Note:

1. To straighten the cord, please use a blow dryer (not included) if necessary.
2. Illustration (Fig. 1) on this manual is for installation purposes only. It may or may not be identical to the fixture purchased.

Fig. 1

Set#A-020-110
Mounting Plate x 1pc
Ground Screw x 1pc
Junction box Screw x 2pcs




Fig. 2





Fig.3



a. Hardware Bag

A. Mounting Plate x 1pc

B. Junction Box

Screw x 2pcs

D. Mounting Screw x 2pcs

