

# INSTALLATION INSTRUCTIONS

Item# 562X-869-L

## READ AND SAVE THESE INSTRUCTIONS

**WARNING! SHUT POWER OFF AT FUSE OR CIRCUIT BREAKER.**  
**AVERTISSEMENT! COUPER LE COURANT AU NIVEAU DES FUSIBLES OU DU DISJONCTEUR.**

### HANGING THE FIXTURE (Fig. 1)

1. Shut off power at the fuse box or circuit breaker box and remove the old fixture including the mounting hardware.
2. Carefully unpack your new fixture and lay out all the parts in a clear area. Take care not to misplace any small parts necessary for installation.
3. Loosen screws (A) and separate mounting plate (B) from canopy (D).
4. Secure mounting plate (B) to junction box (H) (Not included) using mounting screws (F) (Size: #8-32N\*25mmL) provided. The side of mounting plate (B) marked "GND" must face out.

### CONNECTING THE WIRES (Fig. 2)

5. Connect the electrical wires as shown in (Fig.2), making sure that all wire connectors are secured. If your junction box has a ground wire (green or bare copper), connect the fixture ground wire to it. Otherwise, connect the fixture ground wire directly to mounting plate (B) using the green screw provided.
6. After wires are connected, tuck them carefully inside junction box.

### FINISH THE INSTALLATION (Fig. 1)

7. Place canopy (D) over mounting plate (B) and secure with screws (A).
8. Gently twist Shade (E) onto the bottom of canopy (D). Do not over tighten.

### Replacing LED module (Fig.3)

The LED module can be replaced by a qualified electrician without cutting of wire and without damage to any decorative element to which the fixture is attached. See installation steps for more details (Fig 3.)

- a. Shut off the power.
- b. To remove fixture from ceiling, loosen screws (A) and canopy (D) from mounting plate (B). Disconnect wire connectors and place fixture on a clean surface.
- c. Gently twist shade (E) out of the bottom of canopy (D).
- d. Loosen screws (I), remove lamp shape (J), and remove LED module (K) from canopy (D).
- e. Reverse steps b-d for installing the new LED module.

Your installation is complete now. Return power to the junction box and test the fixture.

**Note: Illustration (Fig.1) on this manual is for installation purposes only. It may or may not be identical to the fixture purchased.**

**IMPORTANT: FIXTURE SHOULD BE INSTALLED BY A QUALIFIED ELECTRICIAN TO ENSURE PROPER WIRING AND INSTALLATION.**

Dimmable with ELV and/or LED compatible wall dimmer switches.

